

Inter-Office Memorandum

To F Ludolph Date February 13, 1978

From JR Cucinitti Location Palo Alto

Subject Disk Diagnostic Organization SDD/CS/SD

XEROX

Filed on: <Cucinitti>Diskdiag.memo

The Disk Diagnostic pack has two diagnostics written in four different places in anticipation of losing one or more of them. One diagnostic is booted by using just the boot button in the first case, and depressing the **0** key and pushing the boot button in the next. The other diagnostic is booted with the **K** key and boot button, and the **V** key and the boot button.

The diagnostic booted with no keys and the **0** key will write one pass on the disk and then start into a read loop, we call it write once, read forever. To run the diagnostic just type **40001B** (this sets an error breakpoint), **40000P** (sends the Alto to 40000 to fetch the first instruction). The diagnostic booted with the **K** or **V** key will write, read, write, read,..... To run this diagnostic type **1001B** (sets the error breakpoint), **1000P** (fetches the instruction from 1000). To halt the diagnostic just depress the Swat key, this will display four registers, to continue depress the **P** (proceed) key.

The knowledge of the location of the diagnostics in the Alto memory is of some use. The diagnostic booted by the **0** key resides from 40000 thru 42154 and uses memory locations from 1000 thru 37777 for the data handling area. The diagnostic booted by the **K** key resides from 1000 thru 3153 and uses 40000 thru 176777 for the data handling area. The first 777 locations are used to run the display and keyboard and should not be changed. You may note that the listing does not reflect the true memory locations but do indicate the locations relative to the starting locations of the diagnostics.

The debugger located in the first 1000 locations will allow you to modify any memory location and remember it only knows about octal numbers. The commands to the debugger are:

- n/** opens and displays memory location *n*
- cr** inserts the typed information in *n* and closes the location
- _** modifies, closes location *n*, and opens location *n+1*
- ^** modifies, closes location *n*, and opens location *n-1*
- A** displays accumulators 0-3
- nB** set a breakpoint at location *n*
- nD** deletes breakpoint *n* (1-9)
- nP** proceed from this location

When you do get an error you will see something like this:

DATA COMPARE FAILED
0:123456 1:123455 2:012345 3:001612

AC0 = Data that was to be written on the disk
AC1 = Data that was read from the disk (this may indicate a memory problem)
AC2 = Memory location the disk data was written into
AC3 = Of no interest concerns the text on the display

CONTROLLER REPORTS BAD STATUS:
0:002310 1:007541 2:034523 3:001612

AC0 = Of no interest
AC1 = Disk controller status
AC2 = Pointer to disk control block that failed
AC3 = Of no interest concerns the text on the display

See the Alto hardware manual for the organization of the disk command blocks.

To continue from an error breakpoint just type **P**.

Some of the interesting locations in the diagnostic:

0562 Current sector (0-13) updated by the diagnostic
 0563 Minimum sector number
 0564 Maximum sector number
 0565 Current head number (0=upper, 1=lower)
 0566 Minimum head number
 0567 Maximum head number
 0570 Current drive (0 or 1)
 0571 Minimum drive number
 0572 Maximum drive number
 0573 Current track number
 0574 Minimum track (never less than 100)
 0575 Maximum track

These locations may be changed to write only with one head and just in one sector on one track. If **0574** is changed you may write over the boot loader so **never** have it less than **100**.

Some samples of the disk command blocks that are used for alignment:

Four cylinder seek	
1000/2000	2000/1000
1001/0	2001/0
1002/44002	2002/44002
1003/0	2003/0
1004/0	2004/0
1005/0	2005/0
1006/0	2006/0
1007/0	2007/0
1010/0	2010/0
1011/10	2011/50

At this time set location 521 to 1000, when this location has some value other than 0 the disk microcode will go to that location for the disk command block. To halt the loop set location 521 to 0.

Track 0 or restore adjustment	
1000/2000	2000/1000
1001/0	2001/0
1002/44002	2002/44002
1003/0	2003/0
1004/0	2004/0
1005/0	2005/0
1006/0	2006/0
1007/0	2007/0
1010/0	2010/0
1011/0	2011/51

For head alignment set the command block as follows:

1000/1000
 1001/0
 1002/44002
 1003/0
 1004/0
 1005/0
 1006/0
 1007/0
 1010/0
 1011/1510(upper head), 1011/1514(lower head)

The data burst is adjusted with the same block by changing only location 1011.
 1011/1440(upper head), 1011/1444(lower head)

The disk address may be changed at any time and the microcode will do the right thing, so you need not stop the disk (521/0) to switch from one head to the other.

This is the listing of the diagnostic, if the diagnostic is loaded at 1000 then the first address is not 0 but 1000 and the listing reflects the locations relative to 1000, if loaded at 40000 all locations are relative to 40000.

0001 ALTKD

```

;
;
;   ALTO DISK DIAGNOSTIC
;
;   E. MCCREIGHT
;
;
102513 .DALC   SG=SUBL# 0,0,SNC
102512 .DALC   SLE=SUBL# 0,0,SZC
        .TITL   ALTKD
        .NREL
        .EXTN PHIAD,MESSAGE
000001 .TXTM 1
;
;   ALTO CONSTANTS
;
000521 KBCON=521;      DISK BLOCK ADDRESS
000420 DASCON=420;     DISPLAY BLOCK ADDRESS
000452 WWCON=452;      WAKEUPS WAITING ADDRESS
000501 IVCON=501;       VECTOR OF INTERRUPT NEW PC'S
061001 EIR=61001;      OPCODE FOR ENABLE INTERRUPTS
061000 DIR=61000;      OPCODE FOR DISABLE INTERRUPTS
061002 BRI=61002;      OPCODE FOR RETURN FROM INTERRUPT
000527 TRPC=527;       BEFORE A TRAP THE PC GOES HERE
000530 TRPVEC=530;     THE VECTOR OF 37 TRAP LOCATIONS GOES HERE
062000 ERROR=62000;    UNIMPLEMENTED I/O OPERATION WHICH TRAPS
;
;   THE OLD FORMAT OF A DISK CONTROL BLOCK
;
000000 POINTER=        0
000001 STATUS=         1
000002 DSKCOMM=        2
000003 LABEL=          3
000004 DATA=          4
000005 HDRWD=          5
000006 DSKADR=         6
000007 SUCCESS=        7
000010 FAILURE=       10
000011 HEADER=        11
000012 FINISHUP=       12
000013 INTSDONE=       13
000014 SERRS=         14
000015 DCBEND=        15
;
;   INITIALIZE THE DISK
;
00000'000402 INIT:     JMP      .+2;  SKIP OVER ERROR BREAK

00001'002411 BREAK:     JMP@     .RR2;   PUT DEBUGGER BREAKPOINT HERE !!!

00002'006401     JSR@     .+1;  SET UP THE INTERRUPT SYSTEM
00003'001500'     SIZEM
00004'126400     SUB      1,1;  ZERO THE ERROR COUNTER
00005'000406     JMP      INITA;  SKIP OVER THE DISPLAY CONTROL BLOCK
00006'000000 DB:    0;      MUST BE AN EVEN ADDRESS
0002  ALTKD

```

```

00007'000040      40
00010'000000 DBMP:      0
00011'000536      350.

00012'001473'.RR2:      RR2

00013'044011-INITA:      STA      1,SERRCNT;  ZERO SOFT ERROR COUNT
00014'044012-      STA      1,HERRCNT;      AND HARD ERROR COUNT
00015'022433      LDA@      0,.RBOT;      REASON TABLE RESET TO EMPTY
00016'042433      STA@      0,.RTOP
00017'006401      JSR@      .+1
00020'001042'      SUINT
00021'030004-      LDA      2,KBLKADR;      SET UP ILLEGAL CURRENT ADRESS TO
00022'020425      LDA      0,ALLONES;  FORCE A SEEK
00023'041002      STA      0,2,2
00024'030003-      LDA      2,DASTART
00025'020425      LDA      0,DBLKAD
00026'041000      STA      0,0,2;      START THE DISPLAY
00027'006424      JSR@      SDBAD;      SET UP DISK CONTROL BLOCK CHAINS
00030'101010      MOV#      0,0;      NOP
00031'002401 REDO:      JMP@      .+1
00032'000033'      WRTIT

00033'006456 WRTIT:      JSR@      SMAD
00034'000446      JMP      IDONE
00035'030417 IMORE:      LDA      2,WRTBLK;  SET UP TO WRITE AT CURRENT DISK ADDRESS
00036'004466      JSR      MKDCB
00037'101010      MOV#      0,0;      NOP
00040'006453      JSR      @ARGEN;      INITIALIZE DATA BLOCK
00041'101010      MOV#      0,0;      NOP
00042'006401      JSR@      .+1;  ENTER CPTR IN COMMAND QUEUE
00043'000414'      EQU
00044'006446      JSR@      IAD;      GET THE NEXT DISK ADDRESS
00045'000415      JMP      RDIT;      IF NONE EXIST, READ THE RECORDS
00046'000767      JMP      IMORE;      OTHERWISE, DO IT AGAIN
00047'177777 ALLONES:      177777
00050'000356'.RBOT:      RSNBOT
00051'000400'.RTOP:      RSNTOP
00052'000006'DBLKAD:      DB
00053'000775'SDBAD:      SUDB
00054'000055'WRTBLK:      .+1
00055'000106'      WRTALL
00056'000107'      IHDR
00057'000001-      CODAD
00060'000110'      NOPAD
00061'000601'ANOERR:      NOERR

;
;      READ ALL RECORDS ON THE DISK AND COMPARE THEM WITH WHAT
;      WAS WRITTEN
;

00062'006427 RDIT:      JSR@      SMAD;  GO BACK TO THE MINIMUM DISK ADDRESS
00063'000417      JMP      IDONE;  (IF ERROR)
00064'030406 RDMORE:      LDA      2,RDBLK;  READ A BLOCK AT THE CURRET ADDRESS
00065'004427      JSR      DODCB
00066'101010      MOV#      0,0;  NOP
00067'006423      JSR@      IAD;      GET NEXT DISK ADDRESS
0003  ALTKD

```

```

00070'000412    JMP    IDONE;  IF WE ARE AT THE END, EMPTY THE QUEUE
00071'000773    JMP    RDMORE;  OTHERWISE GET A NEW QUEUE ENTRY AND TAKE OFF

00072'000073'RDBLK:    .+1
00073'000077'    CHRR
00074'000101'    SUBST
00075'000001-    CODAD
00076'000100'    ACDAT

00077'000120 CHRR:    120; CHECK HEADER AND LABEL, READ REST OF SECTOR
00100'000615'ACDAT:    CDAT;
00101'000000 SUBST:    0

00102'006401 IDONE:    JSR@    .+1; MAKE SURE COMMAND QUEUE EMPTIES
00103'000464'    FLUSH
00104'002401 SMASH:    JMP@    .+1
00105'000031'    REDO

00106'000374 WRTALL:    374
00107'171717 IHDR:    171717
00110'000602'NOPAD:    CKDERR;
00111'000474'SMAD:    SETMIN
00112'000506'IAD:    INCAD
00113'000650'ARGEN:    RGEN

;
;    MAKE UP A DISK CONTROL BLOCK AND QUEUE IT FOR THE DISK
;
00114'054407 DODCB:    STA    3,R3DOD
00115'004407    JSR MKDCB;    MAKE UP THE PROPER DCB
00116'101010    MOV#    0,0; NOP
00117'006401    JSR@    .+1; QUEUE IT
00120'000414'    EQU
00121'034402    LDA    3,R3DOD
00122'001401    JMP    1,3

00123'000000 R3DOD:    0

;
;    MAKE UP A DISK CONTROL BLOCK. REGISTER 2 CONTAINS A POINTER
;    TO A FOUR-WORD BLOCK OF POINTERS TO ITEMS TO BE INCLUDED
;    IN THE CONTROL BLOCK: (0) THE DISK COMMAND
;    (1) THE HEADER WORD
;    (2) THE DISK ADDRESS
;    (3) THE FINISHUP ROUTINE
;
00124'054422 MKDCB:    STA    3,R3MKD
00125'050422    STA    2,MKDPARM
00126'004422    JSR GCB;    GET AN AVAILABLE COMMAND BLOCK
00127'101010    MOV#    0,0; NOP
00130'030002-    LDA    2,CPTR;  THE COMMAND BLOCK
00131'034416    LDA    3,MKDPARM
00132'023400    LDA@    0,0,3;  THE DISK COMMAND
00133'041002    STA    0,DSKCOMM,2
0004 ALTKD

```

```

00134'023401   LDA@   0,1,3;   THE HEADER WORD
00135'041005   STA     0,HDRWD,2
00136'023402   LDA@   0,2,3;   THE DISK ADDRESS
00137'041006   STA     0,DSKADR,2
00140'023403   LDA@   0,3,3;   THE FINISHUP ROUTINE
00141'041012   STA     0,FINISHUP,2
00142'102400   SUB     0,0; MARK BLOCK AS UNPROCESSED BY INTERRUPT
00143'041013   STA     0,INTSDONE,2;   ROUTINE
00144'034402   LDA     3,R3MKD
00145'001401   JMP     1,3

```

```

00146'000000 R3MKD:      0
00147'000000 MKDPARM: 0

```

```

;
;   GET A POINTER TO AN AVAILABLE COMMAND BLOCK IN CPTR. ALWAYS
SKIPS.
;

```

```

00150'054414 GCB:   STA     3,R3G
00151'030005-GC1:   LDA     2,AS;   TRY TO ALLOCATE ONE FROM AVAILABLE STACK
00152'151015   MOV#    2,2,SNR;
00153'000406   JMP     STKEMP
00154'025000   LDA     1,POINTER,2;   POP THE AVAILABLE STACK
00155'044005-   STA     1,AS
00156'050002-   STA     2,CPTR
00157'034405   LDA     3,R3G
00160'001401   JMP     1,3

```

```

00161'004404 STKEMP:   JSR   GETQE
00162'000767   JMP     GC1
00163'000766   JMP     GC1

```

```

00164'000000 R3G:      0

```

```

;
;   REMOVE A FINISHED ENTRY FROM THE COMMAND QUEUE, AND PUT
;   IT IN THE AVAILABLE STACK. ALWAYS SKIP.
;

```

```

00165'054557 GETQE:   STA     3,R3Q
00166'101010 GQ1:   MOV#    0,0; NOP
00167'030006-   LDA     2,KQF;   CHECK IF COMMAND QUEUE IS EMPTY. IF SO GIVE ERROR
00170'151015   MOV#    2,2,SNR;
00171'002553   JMP@    R3Q;   DON'T SKIP IF ERROR
00172'025001   LDA     1,STATUS,2;   CHECK THE STATUS OF THE QUEUE FRONT
00173'125014   MOV#    1,1,SZR
00174'000535   JMP     PULLIT;   CONTROLLER GOT TO IT
00175'034004-   LDA     3,KBLKADR;   MAKE SURE CONTROLLER IS RUNNING
00176'021400   LDA     0,0,3
00177'101004   MOV     0,0,SZR
00200'000766   JMP     GQ1;   IT'S RUNNING. RETRY.
00201'021001   LDA     0,STATUS,2;   GET THE STATUS WORD FOR KQF
00202'101014   MOV#    0,0,SZR
00203'000763   JMP     GQ1;   COMMAND AT KQF IS DONE. PROCESS IT.
00204'050007-RES:   STA     2,KQM;   (FOR THE INTERRUPT ROUTINE)
00205'051400   STA     2,0,3;   DISK CONROLLER IS STOPPED AND HAS NOT PROCESSED
00206'000760   JMP     GQ1;   THE COMMAND AT KQF. RESTART IT.

```

```

0005 ALTKD

```

```

00207'010011-AAUGH:  ISZ  SERRCNT;   THERE WAS AN ERROR. ADD ONE TO SOFT
00210'101010      MOV#  0,0;      ERROR COUNT.

00211'022004-     LDA@   0,KBLKADR;   WAIT FOR CONTROLLER TO STOP
00212'101014      MOV#  0,0,SZR
00213'000776      JMP    -2

00214'034542      LDA    3,RSNBOT;   CLASSIFY THE ERROR
00215'020563 SRCHLP: LDA    0,RSNTOP
00216'116512      SLE  0,3
00217'000421      JMP    LOOK

00220'020557      LDA    0,RSNEND;   THIS ERROR NOT IN TABLE
00221'116513      SG   0,3
00222'000434      JMP    HARDYET;   AND NO TABLE SPACE IS LEFT, SIGH!

00223'021001      LDA    0,STATUS,2;  MAKE TABLE ENTRY FOR THIS ERROR
00224'041400      STA    0,0,3
00225'102400      SUB    0,0
00226'041401      STA    0,1,3

00227'161400      INC  3,0;  MOVE UP THE TOP OF THE TABLE
00230'101400      INC  0,0
00231'040547      STA    0,RSNTOP

00232'054513      STA    3,R3SL;    A NEW ERROR STATUS IS SEEN
00233'025001      LDA    1,STATUS,2;  SHOW STATUS TO DIAGNOSTICIAN
00234'006000-     JSR@   PMSG
00235'002135'     NEWER
00236'034507      LDA    3,R3SL
00237'062000      ERROR

00240'021001 LOOK:  LDA    0,STATUS,2;  SEE IF OUR STATUS MATCHES TABLE,
00241'024507      LDA    1,NOKCON;   EXCEPT FOR SECTOR NUMBER
00242'123400      AND    1,0
00243'025400      LDA    1,0,3
00244'106400      SUB    0,1
00245'020503      LDA    0,NOKCON
00246'107405      AND    0,1,SNR
00247'000404      JMP    EFND;       YES, IT DOES
00250'175400      INC  3,3;         NO, IT DOESN'T. GO TO NEXT ENTRY.
00251'175400      INC  3,3
00252'000743      JMP    SRCHLP

00253'021401 EFND:  LDA    0,1,3;         INCREMENT NUMBER OF OCCURRENCES
00254'101400      INC  0,0
00255'041401      STA    0,1,3

00256'021014 HARDYET: LDA    0,SERRS,2;  NUMBER OF SOFT ERRORS FOR THIS BLOCK
00257'101400      INC  0,0
00260'041014      STA    0,SERRS,2

00261'024470      LDA    1,HARDTH;   HAS SOFT ERROR HARDENED?
00262'106513      SG   0,1
00263'000407      JMP    SOFT

00264'010012-     ISZ  HERRCNT;   YES, SEND MESSAGE TO THAT EFFECT
00265'101010      MOV#  0,0
00266'006000-     JSR@   PMSG
0006  ALTKD

```



```

00267'002116'  HARDERR
00270'062000  ERROR

00271'000444  JMP      REMOVE;          GIVE UP ON THIS DCB AND TRY THE NEXT ONE

00272'024460  SOFT:    LDA      1,RESTH;    SHOULD WE DO A RESTORE?
00273'106513      SG  0,1
00274'000423  JMP      AGAIN;          NO, JUST RETRY.

00275'021006  LDA      0,DSKADR,2;    YES, FIGURE OUT WHICH DISK IS INVOLVED
00276'025002  LDA      1,DSKCOMM,2
00277'127000  ADD      1,1
00300'123000  ADD      1,0
00301'024452  LDA      1,DSKBIT
00302'123400  AND      1,0

00303'024451  LDA      1,RSTBIT;    COMPUTE A RESTORE DISK ADDRESS BY
00304'123000  ADD      1,0;    ADDING RESTORE BIT TO BIT FOR AFFECTED
00305'040506  STA      0,RKADR;    DISK.

00306'034004-  LDA      3,KBLKADR;    FORCE A SEEK ON NEXT OPERATION
00307'024446  LDA      1,MONE
00310'045402  STA      1,2,3

00311'020470  LDA      0,,RESTOR;    START THE DISK CONTROLLER ON A RESTORE
00312'041400  STA      0,0,3

00313'021400  LDA      0,0,3;    HAS IT STOPPED YET?
00314'101014  MOV#     0,0,SZR
00315'000776  JMP      -2;    NO -- ASK AGAIN.

00316'045402  STA      1,2,3;    FORCE A SEEK ON NEXT OPERATION

00317'050427  AGAIN:   STA      2,R2ZAP;    SCAN THE CHAIN, RESETTNG DCBS
00320'151005  ZAPLP:   MOV      2,2,SNR
00321'000405  JMP      RESTART
00322'006401  JSR@     .+1;    CLEAR DCB FOR RE-ENTRY ON QUEUE
00323'001565'  SETLAB
00324'031000  LDA      2,POINTER,2
00325'000773  JMP      ZAPLP

00326'030420  RESTART: LDA      2,R2ZAP
00327'034004-  LDA      3,KBLKADR
00330'000654  JMP      RES

00331'006401  PULLIT:  JSR@     .+1;    VERIFY THAT THE CORRECT INTERRUPT
00332'001442'  CKINT;   HAPPENED ON THIS BLOCK
00333'007012  JSR@     FINISHUP,2;    DO THE FINISHUP ROUTINE
00334'000653  JMP      AAUGH;    THINGS DID NOT GO SO WELL
00335'035000  REMOVE:  LDA      3,POINTER,2;    GET NEXT QUEUE FRONT ADDRESS
00336'054006-  STA      3,KQF
00337'024005-  LDA      1,AS;    PUSH THE ENTRY ON AVAILABLE STACK
00340'045000  STA      1,POINTER,2;
00341'050005-  STA      2,AS
00342'034402  LDA      3,R3Q
00343'001401  JMP      1,3

00344'000000  R3Q:    0
00345'000000  R3SL:   0
0007  ALTKD

```

```

00346'000000 R2ZAP:      0
00347'170000 OKCON:     170000
00350'007777 NOKCON:      7777
00351'000010 HARDTH:     10;  NUMBER OF SOFT ERRORS TO HARDEN
00352'000003 RESTH:      3;  NUMBER OF SOFT ERRORS TO TRIGGER RESTORE
00353'000002 DSKBIT:      2
00354'000001 RSTBIT:      1
00355'177777 MONE:       177777

```

```

00356'000357'RSNBOT:     .+1
      000020      .BLK    20;  ERRORS ARE CATEGORIZED IN THIS TABLE:
      ;              (0) ERROR STATUS (EXCEPT FOR SECTOR NO.)
      ;              (1) NUMBER OF OCCURRENCES
00377'000377'RSNEND:      .
00400'000000 RSNTOP:      0

```

```

00401'000402'.RESTOR:    .+1
00402'000000      0
00403'000000      0
00404'044002     44002
00405'000000      0
00406'000000      0
00407'000000      0
00410'000000      0
00411'000000      0
00412'000000      0
00413'000000 RKADR:      0

```

```

;
;  PLACE AN ENTRY IN THE COMMAND QUEUE AND START THE
;  CONTROLLER IF APPROPRIATE.
;

```

```

00414'054456 EQU:        STA      3,R3F
00415'030002-      LDA      2,CPTR;  THE ENTRY TO BE ADDED
00416'126400      SUB      1,1
00417'045000      STA      1,POINTER,2;  GIVE IT A 0 POINTER AND
00420'045014      STA      1,SERRS,2;  NO SOFT ERRORS
00421'020442      LDA      0,VALID;  MARK THIS AS A VALID COMMAND
00422'025002      LDA      1,DSKCOMM,2
00423'107000      ADD      0,1
00424'045002      STA      1,DSKCOMM,2
00425'006401      JSR@     .+1;  CLEAR STATUS AND INTS DONE AND LABEL BLOCK
00426'001565'      SETLAB

00427'024006-      LDA      1,KQF
00430'125014      MOV#     1,1,SZR;  CHECK QUEUE FOR EMPTINESS
00431'000405      JMP      NOTEMP
00432'050006-      STA      2,KQF;  STORE THIS ENTRY IN QUEUE FRONT IF QUEUE IS EMPTY
00433'034004-      LDA      3,KBLKADR
00434'045400      STA      1,0,3;  IDLE THE DISK CONTROLLER, JUST IN CASE.
00435'000403      JMP      EQCOM
00436'034010-NOTEMP:  LDA      3,KQR
00437'051400      STA      2,POINTER,3;  POINT CURRENT REAR ENTRY TO NEW ENTRY
00440'050010-EQCOM:  STA      2,KQR;  SET REAR POINTER TO NEW ENTRY
0008  ALTKD

```

```

00441'030006-FIRELP:    LDA      2,KQF;   IS THE DISK CONTROLLER QUEUE EMPTY?
00442'151015          MOV#    2,2,SNR
00443'000416          JMP      EQDON;    IF SO, WE ARE DONE
00444'034004-        LDA      3,KBLKADR;   IS THE DISK CONTROLLER RUNNING?
00445'021400          LDA      0,0,3
00446'101014          MOV#    0,0,SZR
00447'000412          JMP      EQDON;    IF SO, WE ARE DONE
00450'021001          LDA      0,STATUS,2; CHECK THE STATUS OF THE QUEUE FRONT
00451'101014          MOV#    0,0,SZR
00452'000404          JMP      EXTRACT;   IF DONE, PULL IT OFF THE QUEUE
00453'050007-        STA      2,KQM;   (FOR THE INTERRUPT ROUTINE)
00454'051400          STA      2,0,3;   START THE DISK CONTROLLER
00455'000404          JMP      EQDON

00456'006415 EXTRACT:JSR@      .GETQE
00457'101010          MOV#    0,0; NOP
00460'000761          JMP      FIRELP

00461'034411 EQDON:      LDA      3,R3F;
00462'001401          JMP      1,3

00463'044000 VALID:      44000

;
;   FLUSH THE COMMAND QUEUE INTO AVAILABLE SPACE AS THE CONTROLLER
;   FINISHES IT.
;
00464'054406 FLUSH:      STA      3,R3F
00465'006406 FL1:      JSR@      .GETQE
00466'000402          JMP      FLDON;   ERROR RETURN MEANS QUEUE IS EMPTY
00467'000776          JMP      FL1
00470'034402 FLDON:      LDA      3,R3F
00471'001401          JMP      1,3

00472'000000 R3F:      0
00473'000165'.GETQE:    GETQE

;
;   POINTERS, COMMAND BLOCKS, AND OTHER GOODIES
;

.ZREL
00000-177777 PMSG:      MESSAGE
00001-000000 CODAD:      0
00002-000000 CPTR:      0
00003-000420 DASTART:DASCON
00004-000521 KBLKADR:KBCON
00005-000000 AS:      0;   TOP OF STACK OF AVAILABLE DCB'S
00006-000000 KQF:      0;   FRONT OF COMMAND QUEUE. 0 MEANS QUEUE IS EMPTY.
00007-000000 KQM:      0;   CURRENT ACTION POINT IN COMMAND QUEUE.
;   USED AND MAINTAINED BY INTERRUPT ROUTINES.
00010-000000 KQR:      0;   REAR OF COMMAND QUEUE.
00011-000000 SERRCNT:    0;   COUNT OF SOFT ERRORS
00012-000000 HERRCNT:    0;   COUNT OF HARD ERRORS
00013-000452 WWLOC:      WWCON
00014-000501 INTVEC:      IVCON

```

0009 ALTKD

.NREL

```

;
; THIS ROUTINE SETS OR INCREMENTS A DISK ADDRESS. IT
; USES A TABLE OF CURRENT, MIN, AND MAX VALUES FOR THE
; VARIOUS FIELDS OF A DISK ADDRESS. ENCODED ADDRESS GOES IN
; CODAD. SKIP IF SUCCESS.
;

```

```

00474'054464 SETMIN:   STA     3,R3T
00475'030464         LDA     2,TABMIN
00476'024500 MINLP:   LDA     1,TABMAX
00477'132513         SG     1,2;  SKIP IF TABMAX>CURTAB
00500'000427         JMP     ENCODE;   DONE
00501'025001         LDA     1,1,2;   GET MIN FOR THIS FIELD
00502'045000         STA     1,0,2;   MAKE IT CURRENT
00503'024474         LDA     1,TABINC
00504'133000         ADD     1,2;  MOVE TO NEXT FIELD
00505'000771         JMP     MINLP

00506'054452 INCAD:   STA     3,R3T
00507'030452         LDA     2,TABMIN
00510'024466 INCLP:   LDA     1,TABMAX
00511'132513         SG     1,2;  SKIP IF TABMAX>CURTAB
00512'000444         JMP     OFFEND;   CARRY PROPAGATED TO NON-EXISTENT FIELD
00513'025000         LDA     1,0,2;   GET CURRENT VALUE FOR THIS FIELD
00514'125400         INC     1,1;  ADD 1
00515'021002         LDA     0,2,2;   GET MAXIMUM VALUE FOR THIS FIELD
00516'122512         SLE     1,0;  IF CURRENT<=MAX, UPDATE CURRENT AND QUIT
00517'000403         JMP     CARRY
00520'045000         STA     1,0,2;   UPDATE CURRENT
00521'000406         JMP     ENCODE

00522'025001 CARRY:   LDA     1,1,2;   GET MINIMUM VALUE FOR THIS FIELD
00523'045000         STA     1,0,2;   STORE IT IN CURRENT
00524'024453         LDA     1,TABINC;  MOVE TO NEXT FIELD
00525'133000         ADD     1,2
00526'000762         JMP     INCLP

00527'024433 ENCODE:  LDA     1,SECTOR
00530'125020         MOVZ    1,1;  FORCE A ZERO CARRY
00531'125120         MOVZL   1,1
00532'125120         MOVZL   1,1
00533'125120         MOVZL   1,1
00534'125120         MOVZL   1,1
00535'125120         MOVZL   1,1
00536'125120         MOVZL   1,1
00537'125120         MOVZL   1,1
00540'125120         MOVZL   1,1
00541'125120         MOVZL   1,1
00542'030431         LDA     2,CYL
00543'147000         ADD     2,1
00544'125120         MOVZL   1,1
00545'030420         LDA     2,HEAD
00546'147000         ADD     2,1
00547'125120         MOVZL   1,1
00550'030420         LDA     2,DSKNO
00551'147000         ADD     2,1
00552'125120         MOVZL   1,1
0010 ALTKD

```

```

00553'044001-   STA      1,CODAD
00554'034404   LDA      3,R3T
00555'001401   JMP      1,3

00556'034402 OFFEND:   LDA      3,R3T
00557'001400   JMP      0,3

00560'000000 R3T:      0
00561'000562'TABMIN:   SECTOR
00562'000000 SECTOR:   0
00563'000000          0
00564'000013          13
00565'000000 HEAD:     0
00566'000000          0
00567'000001          1
00570'000000 DSKNO:     0
00571'000000          0
00572'000000          0
00573'000000 CYL:      0
00574'000100          100; DON'T WIPE OUT THE BOOT AREA
00575'000312          312
00576'000576'TABMAX:   .
00577'000003 TABINC:    3
00600'000001 C1:       1

;
;   REGARDLESS OF THE FINAL STATUS, GIVE A SKIP RETURN
;
00601'001401 NOERR:     JMP      1,3

;
;   CHECK THAT THE COMMAND COMPLETED CORRECTLY.
;

00602'025001 CKDERR:     LDA      1,STATUS,2;  GET THE FINISHING STATUS
00603'020411          LDA      0,ERMSK
00604'107415          AND#     0,1,SNR
00605'001401          JMP      1,3;  CORRECT RETURN
00606'054405          STA 3 CKDRET
00607'006000-         JSR@ PMSG
00610'001616'         CDER
00611'062000          ERROR
00612'002401          JMP@ CKDRET

00613'000000 CKDRET:     0

00614'000277 ERMSK:      277

;
;   COMPARE THE RECORD READ WITH THE ONE ORIGINALLY WRITTEN
;
00615'054427 CDAT:       STA      3,R3C
00616'004764          JSR  CKDERR;  CHECK THE STATUS
0011  ALTKD

```

```

00617'002425    JMP@    R3C;    IF ERROR
00620'050422    STA      2,R2C
00621'021005    LDA      0,HDRWD,2
00622'024421    LDA      1,IHDR1
00623'106414    SUB#     0,1,SZR; CHECK THAT SUBSTITUTION REALLY WORKS
00624'000406    JMP      LNOTEQ
00625'006422    JSR @ARTST; COMPARE THE RANDOM DATA
00626'000411    JMP      NOTEQ; IF ERROR
00627'030413    LDA      2,R2C; COMPARE IS OK
00630'034414    LDA      3,R3C
00631'001401    JMP      1,3

00632'061000 LNOTEQ:    DIR
00633'006000-    JSR@ PMSG
00634'001641'    LFAIL
00635'061001    EIR
00636'062000    ERROR
00637'030403 NOTEQ:    LDA      2,R2C
00640'034404    LDA      3,R3C
00641'001400    JMP      0,3

00642'000000 R2C:      0
00643'171717 IHDR1:    171717
00644'000000 R3C:      0
00645'000010 C8:       10
00646'000400 C256:     400
00647'000732 ARTST:    RTST

;
; RANDOM DATA GENERATOR -- GENERATES INTO LAB AND DAT
;
00650'054447 RGEN:     STA      3,R3RG
00651'050447    STA      2,R2RG
00652'024440    LDA      1,DWDMX
00653'044440    STA      1,DWDCT
00654'031003    LDA      2,LABEL,2; R2 POINTED TO THE DCB
00655'034444    LDA      3,APRO
00656'024436    LDA      1,PRMX; COPY THE STARTUP PARAMETERS TO THE
00657'044436    STA      1,PRCT; LABEL BLOCK

00660'025400 RGLPO:    LDA      1,0,3
00661'045000    STA      1,0,2
00662'151400    INC 2,2
00663'175400    INC 3,3
00664'014431    DSZ      PRCT
00665'000773    JMP      RGLPO

00666'030432    LDA      2,R2RG
00667'031004    LDA      2,DATA,2; ADDRESS OF DATA BLOCK
00670'102400    SUB      0,0

00671'024423 RGLP:     LDA      1,PRMX
00672'044423    STA      1,PRCT
00673'034426    LDA      3,APRO

00674'025400 RGLPA:    LDA      1,0,3
00675'123000    ADD      1,0
0012 ALTKD

```

```

00676'041400    STA      0,0,3
00677'041000    STA      0,0,2
00700'014413    DSZ      DWDCT
00701'151401    INC      2,2,SKP
00702'000405    JMP      RGOK
00703'014412    DSZ      PRCT
00704'175401    INC      3,3,SKP
00705'000764    JMP      RGLP
00706'000766    JMP      RGLPA

00707'034410 RGOK:    LDA      3,R3RG
00710'030410    LDA      2,R2RG
00711'001401    JMP      1,3

00712'000400 DWDMX:    400
00713'000000 DWDCT:    0
00714'000010 PRMX:     10
00715'000000 PRCT:     0
00716'000000 RBEGAD:   0
00717'000000 R3RG:     0
00720'000000 R2RG:     0
00721'000722'APRO:     PRO
00722'177777 PRO:      177777
00723'166666    166666
00724'155555    155555
00725'144444    144444
00726'133333    133333
00727'122222    122222
00730'111111    111111
00731'100000    100000

;
;   RANDOM DATA TEST ROUTINE
;
00732'054765 RTST:    STA      3,R3RG
00733'050765    STA      2,R2RG
00734'024756    LDA      1,DWDMX
00735'044756    STA      1,DWDCT
00736'025003    LDA      1,LABEL,2
00737'044757    STA      1,RBEGAD
00740'031004    LDA      2,DATA,2
00741'102400    SUB      0,0

00742'024752 RTLP:    LDA      1,PRMX
00743'044752    STA      1,PRCT
00744'034752    LDA      3,RBEGAD

00745'025400 RTLPA:   LDA      1,0,3
00746'123000    ADD      1,0
00747'041400    STA      0,0,3
00750'025000    LDA      1,0,2
00751'106414    SUB#     0,1,SZR
00752'000410    JMP      RTERR
00753'014740    DSZ      DWDCT
00754'151401    INC      2,2,SKP
00755'000415    JMP      RTOK
00756'014737    DSZ      PRCT
00757'175401    INC      3,3,SKP
0013 ALTKD

```

```

00760'000762    JMP    RTLP
00761'000764    JMP    RTLPA

```

```

00762'061000 RTERR:    DIR
00763'006000-    JSR@ PMSG
00764'001664'    DATF
00765'061001    EIR
00766'062000    ERROR
00767'034730    LDA     3,R3RG
00770'030730    LDA     2,R2RG
00771'001400    JMP     0,3

```

```

00772'034725 RTOK:    LDA     3,R3RG
00773'030725    LDA     2,R2RG
00774'001401    JMP     1,3

```

```

;
;   THIS ROUTINE SETS UP DISK DATA AND CONTROL BLOCKS

```

```

00775'054434 SUDB:    STA     3,R3SUD
00776'020434    LDA 0 NBUFS
00777'100400    NEG     0,0
01000'176400    SUB     3,3; SET UP ZERO LINK FOR FIRST BLOCK
01001'030432    LDA     2 FIRBUF
01002'055000 SULP:    STA     3,POINTER,2;    SET STACK LINK
01003'034431    LDA     3,HDRDIS
01004'157000    ADD     2,3
01005'055011    STA     3,HEADER,2;    SET HEADER LINK
01006'034427    LDA     3,DCBLEN
01007'157000    ADD     2,3
01010'055003    STA     3,LABEL,2;    SET LABEL LINK
01011'034425    LDA     3,DLEN
01012'157000    ADD     2,3
01013'055004    STA     3,DATA,2;    SET DATA LINK
01014'034424    LDA     3,CS2;    SUCCESS INTERRUPT
01015'055007    STA     3,SUCCESS,2
01016'034423    LDA     3,CS4;    FAILURE INTERRUPT
01017'055010    STA     3,FAILURE,2
01020'155000    MOV     2,3; CURRENT BLOCK BECOMES OLD BLOCK
01021'030416    LDA     2,BLKLEN;    LENGTH OF A BLOCK
01022'173000    ADD     3,2; ADDRESS OF NEW BLOCK
01023'101404    INC 0,0,SZR; DONE ENOUGH BLOCKS YET?
01024'000756    JMP     SULP;    NO
01025'054005-    STA     3,AS;    SET UP THE AVAILABLE STACK
01026'040006-    STA     0,KQF;    THE DISK QUEUE IS EMPTY
01027'034402    LDA     3,R3SUD
01030'001401    JMP     1,3

```

```

01031'000000 R3SUD:    0
01032'000000 NBUFS:    0
01033'000000 FIRBUF:    0
01034'000005 HDRDIS:    HDRWD-POINTER
01035'000015 DCBLEN:    DCBEND-POINTER
01036'000025 DLEN:      DCBEND-POINTER+10
01037'000425 BLKLEN:    DCBEND-POINTER+10+400
01040'000002 CS2:      2
01041'000004 CS4:      4
0014 ALTKD

```



```

;
;   SET UP AND ENABLE INTERRUPTS
;
01042'054450 SUINT:    STA      3,R3SU
01043'034455    LDA      3,ATRVEC;  INITIALIZE TRAP VECTOR TO
01044'020453    LDA      0,CS40;    JMP@ TRPC
01045'040455    STA      0,ISUCNT
01046'020453    LDA      0,ARETROU
01047'041400 TSULP:    STA      0,0,3
01050'175400    INC      3,3
01051'014451    DSZ      ISUCNT
01052'000775    JMP      TSULP
01053'034004-   LDA      3,KBLKADR
01054'020440    LDA      0,CS10;  TURN ON DISK SECTOR INTERRUPTS
01055'041403    STA      0,3,3
01056'020451    LDA      0,ABADINT
01057'034014-   LDA      3,INTVEC
01060'024435    LDA      1,NBADI
01061'044441    STA      1,ISUCNT
01062'024431    LDA      1,CY1
01063'030433    LDA      2,DBUGAD;  DON'T MESS WITH THE DEBUGGER'S INT
01064'156414 ISULP:    SUB#      2,3,SZR;  SKIP OVER DEBUGGER INTERRUPT
01065'041400    STA      0,0,3;    INITIALLY MARK ALL INTERRUPTS AS BAD
01066'175400    INC      3,3
01067'122400    SUB      1,0;      THIS LETS US FIND OUT WHICH INTERRUPT
01070'014432    DSZ      ISUCNT
01071'000773    JMP      ISULP
01072'034014-   LDA      3,INTVEC;  NOW FILL IN THE GOOD INTERRUPTS
01073'020430    LDA      0,ASIR;    THE SECTOR INTERRUPT ROUTINE
01074'041403    STA      0,3,3
01075'020427    LDA      0,AXER;    TRANSFER ERROR ROUTINE
01076'041402    STA      0,2,3
01077'020426    LDA      0,AXNER;   TRANSFER NO-ERROR ROUTINE
01100'041401    STA      0,1,3

01101'034013-   LDA      3,WWLOC;  ENABLE ALL INTERRUPTS
01102'102400    SUB      0,0
01103'041401    STA      0,1,3;    MASK OFF ALL INTERRUPTS
01104'061001    EIR
01105'041400    STA      0,0,3;    WIPE OUT PENDING INTERRUPTS
01106'020420    LDA      0,ALLINTS
01107'041401    STA      0,1,3;    UNMASK ALL INTERRUPTS

01110'034402    LDA      3,R3SU
01111'001401    JMP      1,3

01112'000000 R3SU:    0
01113'000001 CY1:    1
01114'000010 CS10:   10
01115'000020 NBADI:  20;  NUMBER OF INTERRUPTS
01116'000517 DBUGAD:  IVCON+16;  DEBUGGER'S INTERRUPT
01117'000040 CS40:   40
01120'000530 ATRVEC:  TRPVEC
01121'001466 ARETROU: RETROU
01122'000000 ISUCNT:  0
01123'001263 ASIR:    SIR
01124'001350 AXER:    XER
01125'001267 AXNER:   XNER
0015 ALTKD

```

01126'177777 ALLINTS: 177777
 01127'001150'ABADINT: BADINT

```

;
;   BAD INTERRUPT. THIS SHOULDN'T HAPPEN.
;
01130'010522   ISZ   WHY
01131'010521   ISZ   WHY
01132'010520   ISZ   WHY
01133'010517   ISZ   WHY
01134'010516   ISZ   WHY
01135'010515   ISZ   WHY
01136'010514   ISZ   WHY
01137'010513   ISZ   WHY
01140'010512   ISZ   WHY
01141'010511   ISZ   WHY
01142'010510   ISZ   WHY
01143'010507   ISZ   WHY
01144'010506   ISZ   WHY
01145'010505   ISZ   WHY
01146'010504   ISZ   WHY
01147'010503   ISZ   WHY
01150'054574 BADINT:   STA       3,R3XX
01151'006401   JSR@    .+1
01152'001376'   IREE
01153'020477   LDA     0,WHY;   IS THIS A PARITY INTERRUPT?
01154'101014   MOV#    0,0,SZR
01155'000463   JMP     NONPAR

01156'022475 PARITY:   LDA@    0,,DSPL;   SAVE THE DISPLAY POINTER
01157'040475   STA     0,ODSPL

01160'102400   SUB     0,0;      TURN OFF THE DISPLAY
01161'042472   STA@    0,,DSPL

01162'020475   LDA     0,BIGNO;   WAIT FOR DISPLAY TO QUIESCE
01163'040475   STA     0,DLY
01164'014474   DSZ     DLY
01165'000777   JMP     -1

01166'022004-   LDA@    0,KBLKADR;   WAIT FOR THE DISK TO STOP
01167'101014   MOV#    0,0,SZR
01170'000776   JMP     -2

01171'061000   DIR;      TURN OFF PARITY BIT IN WW
01172'022464   LDA@    0,,WW
01173'024462   LDA     1,PARCON
01174'124000   COM     1,1
01175'123400   AND     1,0
01176'042460   STA@    0,,WW
01177'061001   EIR

01200'152400   SUB     2,2;      SET UP FOR A MEMORY PASS TO LOOK FOR PARITY
01201'050461   STA     2,NFND;   NUMBER OF ERRORS FOUND ON THIS PASS
01202'020457   LDA     0,LIMIT
01203'040455   STA     0,DLY

01204'021000 PARLP:   LDA     0,0,2;   PICK UP A WORD
0016 ALTKD

```

```

01205'101000    MOV 0 0          ;GIVE THE INTERRUPT TIME TO TRY TO HAPPEN
01206'026450    LDA 1 @.WW
01207'125212    MOVR# 1 1 SZC
01210'000416    JMP      FNDIT;   YES .. AC2 POINTS TO THE CULPRIT

01211'151400 PARNX:    INC 2,2; NO .. TRY NEXT WORD
01212'014446    DSZ      DLY
01213'000771    JMP      PARLP

01214'020440    LDA      0,ODSPL;   START UP THE DISPLAY AGAIN
01215'042436    STA@     0,,DSPL

01216'020444    LDA      0,NFND;     IF AT LEAST ONE ERROR WAS FOUND, IT
01217'101004    MOV      0,0,SZR;   WAS NOT A PHANTOM
01220'000424    JMP      REINT

01221'061000    DIR
01222'006000-   JSR@ PMSG
01223'001701'   NOPE
01224'062000    ERROR;     PARITY ERROR, NO BAD WORD FOUND

01225'000417    JMP      REINT

01226'010434 FNDIT:    ISZ  NFND;   WE FOUND ANOTHER ERROR
01227'061000    DIR
01230'006000-   JSR@ PMSG
01231'001717'   REALP
01232'062000    ERROR;     PARITY ERROR AC2 POINTS TO BAD WORD, AC0 HAS DATA READ
01233'022423    LDA 0 @.WW      ;TURN OFF THE P.E. BIT IN WW
01234'101200    MOVR 0 0
01235'101120    MOVZL 0 0
01236'042420    STA 0 @.WW

01237'000752    JMP      PARNX; TRY FOR ANOTHER BAD WORD

01240'061000 NONPAR:   DIR
01241'006000-   JSR@ PMSG
01242'001735'   XXI
01243'062000    ERROR;     UNEXPECTED INTERRUPT, NOT PARITY

01244'010406 REINT:    ISZ  WHY;    MAKE SURE WHY IS POSITIVE
01245'014405    DSZ      WHY
01246'000777    JMP      .-1
01247'034475    LDA      3,R3XX
01250'002401    JMP@     .+1
01251'001425'   IRET

01252'000000 WHY:      0
01253'000420 .DSPL:    420
01254'000000 ODSPL:    0
01255'000001 PARCON:   1
01256'000452 .WW:      452
01257'177777 BIGNO:    177777
01260'000000 DLY:      0
01261'137777 LIMIT:    137777
01262'000000 NFND:     0;   NUMBER OF ERRORS FOUND ON THIS PASS

;
;   SECTOR INTERRUPT ROUTINE. ADD ONE TO SECTOR COUNTER AND
0017 ALTKD

```

```

; RETURN.
;
01263'010403 SIR: ISZ SECTCNT
01264'101010 MOV# 0,0; NOP
01265'061002 BRI

01266'000000 SECTCNT: 0

;
; TRANSFER NO-ERROR ROUTINE
;
01267'054455 XNER: STA 3,R3XX
01270'006401 JSR@ .+1
01271'001376' IREE
01272'030007- LDA 2,KQM
01273'021001 LDA 0,STATUS,2; PICK UP THE DCB'S STATUS
01274'024451 LDA 1,CX7677
01275'123400 AND 1,0
01276'024450 LDA 1,CX7400
01277'106415 SUB# 0,1,SNR
01300'000404 JMP .+4
01301'006000- JSR@ PMSG
01302'001753' WRSTAT
01303'062000 ERROR; ERROR STATUS OR NO STATUS
01304'024443 LDA 1,CX1; NEW INTERRUPT PROCESSED WORD
01305'021013 XCOM: LDA 0,INTSDONE,2; GET OLD INTERRUPT PROCESSED WORD
01306'101015 MOV# 0,0,SNR; SHOULD BE 0
01307'000404 JMP .+4
01310'006000- JSR@ PMSG
01311'002001' IAP
01312'062000 ERROR; ALREADY PROCESSED BY INTERRUPT
01313'045013 STA 1,INTSDONE,2; STORE NEW VALUE
01314'031000 LDA 2,POINTER,2; MOVE TO NEXT COMMAND BLOCK
01315'050007- STA 2,KQM
01316'151015 MOV# 2,2,SNR; CHECK FOR NULL LINK
01317'000422 JMP XRET
01320'021001 LDA 0,STATUS,2; GET THE STATUS OF THE OPERATION
01321'101015 MOV# 0,0,SNR
01322'000417 JMP XRET; NOT YET FINISHED
01323'024422 LDA 1,CX7677; ENSURE THAT THE INTERRUPT HAPPENS
01324'123400 AND 1,0
01325'024421 LDA 1,CX7400
01326'106414 SUB# 0,1,SZR
01327'000403 JMP XER1
01330'021007 LDA 0,SUCCESS,2; GET NO-ERROR INTERRUPT WORD
01331'000402 JMP XSHR
01332'021010 XER1: LDA 0,FAILURE,2; GET ERROR INTERRUPT WORD
01333'026013-XSHR: LDA@ 1,WWLOC; OR THE INTERRUPT WORD INTO WW
01334'111000 MOV 0,2
01335'133400 AND 1,2
01336'146400 SUB 2,1
01337'123000 ADD 1,0
01340'042013- STA@ 0,WWLOC
01341'034403 XRET: LDA 3,R3XX
01342'002401 JMP@ .+1
01343'001425' IRET

```

0018 ALTKD

```

01344'000000 R3XX:      0
01345'007677 CX7677:    7677
01346'007400 CX7400:    7400
01347'000001 CX1:       1

```

```

;
;   TRANSFER ERROR INTERRUPT ROUTINE
;
01350'054774 XER:      STA      3,R3XX
01351'006401 JSR@      .+1
01352'001376' IREE
01353'030007- LDA      2,KQM
01354'021001 LDA      0,STATUS,2;  GET THIS DCB'S STATUS
01355'024770 LDA      1,CX7677
01356'123400 AND      1,0
01357'024767 LDA      1,CX7400
01360'106414 SUB#      0,1,SZR
01361'000404 JMP      .+4
01362'006000- JSR@ PMSG
01363'002022' NESE
01364'062000 ERROR;      STATUS IS NO ERROR
01365'123400 AND      1,0
01366'122415 SUB#      1,0,SNR
01367'000404 JMP      .+4
01370'006000- JSR@ PMSG
01371'002050' NSSE
01372'062000 ERROR;      NO STATUS STORED
01373'024402 LDA      1,CX2
01374'000711 JMP      XCOM

```

```

01375'000002 CX2:      2

```

```

;
;   REENABLE DEBUGGER INTERRUPT AND SAVE STATE
;
01376'040421 IREE:      STA      0,R0X
01377'044421 STA      1,R1X
01400'050421 STA      2,R2X
01401'022414 LDA 0 @TPCP      ;SAVE TRAP PC IN CASE WE WERE INTERRUPTED OUT OF A
TRAP
01402'040414 STA 0 OTPC
01403'030013- LDA      2,WWLOC
01404'021001 LDA      0,1,2;      SAVE CURRENT INTERRUPT MASK
01405'040415 STA      0,CMASK
01406'020415 LDA      0,DBMSK
01407'041001 STA      0,1,2;      SET NEW MASK FOR ONLY DEBUGGER
01410'030014- LDA      2,INTVEC
01411'021377 LDA      0,-1,2;      SAVE INTERRUPT OLD PC
01412'040412 STA      0,OLDPC
01413'061001 EIR
01414'001401 JMP      1,3

```

```

01415'000527 TPCP:      527
01416'000000 OTPC:      0
01417'000000 R0X:       0
0019  ALTKD

```

```

01420'000000 R1X:      0
01421'000000 R2X:      0
01422'000000 CMASK:    0
01423'040000 DBMSK:    40000;    THE DEBUGGER INTERRUPT ONLY
01424'000000 OLDPC:     0
;
;    REENABLE ALL INTERRUPTS AND RETURN CONTROL TO INTERRUPTED
STUFF
;
01425'061000 IRET:      DIR
01426'020770    LDA 0 OTPC
01427'042766    STA 0 @TPCP
01430'030013-   LDA    2,WWLOC
01431'020771    LDA    0,CMASK
01432'041001    STA    0,1,2;    RESTORE ORIGINAL MASK
01433'030014-   LDA    2,INTVEC
01434'020770    LDA    0,OLDPC
01435'041377    STA    0,-1,2;    RESTORE OLD PC
01436'020761    LDA    0,R0X
01437'024761    LDA    1,R1X;    RESTORE REGISTERS
01440'030761    LDA    2,R2X
01441'061002    BRI
;
;
;    THIS ROUTINE VERIFIES THAT AN INTERRUPT WAS PROCESSED FOR
;    THIS DCB AND THAT ITS TYPE WAS CONSISTENT WITH THE
;    STATUS ENTERED IN THE DCB.
;
01442'054423 CKINT:    STA    3,R3CKS
01443'021001    LDA    0,STATUS,2;    GET THE DCB'S STATUS WORD
01444'024701    LDA    1,CX7677
01445'123400    AND     1,0
01446'024700    LDA    1,CX7400
01447'106414    SUB#    0,1,SZR
01450'000413    JMP     CKIER
01451'024676    LDA    1,CX1;    PROPER INTERRUPT TYPE FOR NO ERROR
01452'021013 CKINCOM: LDA    0,INTSDONE,2;    ACTUAL TYPE
01453'106415    SUB#    0,1,SNR
01454'000405    JMP     .+5
01455'061000    DIR
01456'006000-   JSR@ PMSG
01457'002073'   WINT
01460'062000    ERROR;    WRONG TYPE OR NO TYPE
01461'034404    LDA    3,R3CKS
01462'001401    JMP     1,3

01463'024712 CKIER:    LDA    1,CX2;    PROPER INTERRUPT TYPE FOR ERROR
01464'000766    JMP     CKINCOM

01465'000000 R3CKS:    0

;
;    RETURN FROM TRAP ROUTINE
0020 ALTKD

```

```

;
01466'054407 RETROU:   STA     3,R3RU
01467'036407   LDA@    3,ATRPC
01470'054407   STA     3,LOCPC
01471'002401   JMP@    .+1; JUMP TO BREAKPOINTED INSTRUCTION
01472'000001'   BREAK

01473'034402 RR2:    LDA     3,R3RU
01474'002403   JMP@    LOCPC

01475'000000 R3RU:   0
01476'000527 ATRPC:   TRPC
01477'000000 LOCPC:   0

;SIZE AND PARCEL OUT MEMORY. IF THERE IS SPACE BETWEEN 1000
;AND THE BOTTOM OF THE PROGRAM, WE USE IT FOR DISK BUFFERS
01500'054453 SIZEM:   STA 3 SIZRET
01501'030455   LDA 2 EOM    ;SIZE THE MEMORY
01502'126520   SUBZL 1 1
01503'045001 SIZEL:   STA 1 1 2
01504'021001   LDA 0 1 2
01505'132400   SUB 1 2
01506'122404   SUB 1 0 SZR
01507'000774   JMP SIZEL
01510'052447   STA 2 @PLIM
01511'020443   LDA 0 SOMEM    ;START OF MEMORY
01512'024443   LDA 1 SOP     ;START OF PROGRAM
01513'106414   SUB# 0 1 SZR
01514'000403   JMP SIZED
;OTHERWISE, WE USE SPACE FROM THE END OF THE DEBUGGER TO THE END
OF
;CORE
01515'145000   MOV 2 1
01516'020442   LDA 0 EOP
01517'042442 SIZED:   STA 0 @PBUFS    ;AC0 CONTAINS THE START OF THE BUFFERS,AC1 THE
END
01520'042442   STA 0 @DBMS
01521'036442   LDA@ 3 BUFSZ
01522'152401   SUB 2 2 SKP
01523'151400 BUFL:    INC 2 2
01524'163000   ADD 3 0
01525'106032   ADCZ# 0 1 SZC    ;SKGE
01526'000775   JMP BUFL
01527'052435   STA 2 @NBP    ;AC2 = NUMBER OF BUFFERS WHICH WILL FIT IN THE GIVEN
AREA

;NOW WE GO THROUGH MEMORY AND CORRECT PARITY
01530'061001   EIR
01531'102400   SUB 0 0
01532'042420   STA 0 @UGHX    ;CLEAR NWW
01533'036424   LDA 3 @PLIM
01534'152520   SUBZL 2 2
01535'021400 PQLP:   LDA 0 0 3
01536'041400   STA 0 0 3
01537'025400   LDA 1 0 3
01540'106414   SUB# 0 1 SZR
01541'000401   JMP .+1
01542'026410   LDA 1 @UGHX    ;CHECK FOR ERROR
01543'125213   MOVR# 1 1 SNC
01544'000402   JMP .+2
01545'000401   JMP .+1    ;BREAK HERE TO GET THE BAD NEWS
0021 ALTKD

```

```

01546'156404    SUB 2 3 SZR
01547'000766    JMP PQLP
01550'034403    LDA 3 SIZRET
01551'001401    JMP 1 3

01552'000452    UGHX:      452
01553'000000    SIZRET:    0
01554'001000    SOMEM:     1000
01555'000000    SOP:       INIT
01556'176777    EOM:       176777
01557'001261    PLIM:      LIMIT      ;TOP OF MEMORY FOR PARITY SCAN
01560'177777    EOP:       PHIAD
01561'001033    PBUFS:     FIRBUF
01562'000010    DBMS:      DBMP
01563'001037    BUFSZ:     BLKLEN
01564'001032    NBP:       NBUFS

;
; CLEAR THE STATUS AND INTERRUPTS DONE FIELDS
; IF THE LABEL BLOCK IS TO BE CHECKED, CLEAR IT FIRST
;

01565'054424    SETLAB:    STA      3,R3SET

01566'102400    SUB      0,0
01567'041001    STA      0,STATUS,2;  CLEAR DCB'S STATUS
01570'041013    STA      0,INTSDONE,2;  AND INTERRUPTS PROCESSED

01571'021002    LDA      0,DSKCOMM,2
01572'024420    LDA      1,CKLM
01573'123400    AND      1,0
01574'024417    LDA      1,CKLV
01575'106414    SUB#     0,1,SZR
01576'000411    JMP      ESETLAB;  NOT CHECKING THE LABEL

01577'020415    LDA      0,SL10;  LENGTH OF THE LABEL BLOCK
01600'040415    STA      0,SLCNT

01601'035003    LDA      3,LABEL,2
01602'102400    SUB      0,0

01603'041400    SETLLP:    STA      0,0,3;  CLEAR A WORD
01604'175400    INC      3,3
01605'014410    DSZ      SLCNT
01606'000775    JMP      SETLLP

01607'034402    ESETLAB: LDA      3,R3SET
01610'001401    JMP      1,3

01611'000000    R3SET:     0
01612'000060    CKLM:     60;  MASKS ONLY LABEL PART OF COMMAND
01613'000020    CKLV:     20;  VALUE OF LABEL FIELD IF CHECKING
01614'000010    SL10:     10;  LENGTH OF LABEL BLOCK
01615'000000    SLCNT:     0

CDER:  .TXT      /  CONTROLLER REPORTED BAD STATUS<15>/

01616'020040
0022  ALTKD

```


01617'020040
 01620'020103
 01621'047516
 01622'052122
 01623'047514
 01624'046105
 01625'051040
 01626'051105
 01627'050117
 01630'051124
 01631'042504
 01632'020102
 01633'040504
 01634'020123
 01635'052101
 01636'052125
 01637'051415
 01640'000000

LFAIL: .TXT / LABEL BLOCK SUBSTITUTION FAILED<15>/

01641'020040
 01642'020040
 01643'020114
 01644'040502
 01645'042514
 01646'020102
 01647'046117
 01650'041513
 01651'020123
 01652'052502
 01653'051524
 01654'044524
 01655'052524
 01656'044517
 01657'047040
 01660'043101
 01661'044514
 01662'042504
 01663'006400

DATE: .TXT / DATA COMPARE FAILED<15>/

01664'020040
 01665'020040
 01666'020104
 01667'040524
 01670'040440
 01671'041517
 01672'046520
 01673'040522
 01674'042440
 01675'043101
 01676'044514
 01677'042504
 01700'006400

NOPE: .TXT / PHANTOM PARITY ERROR<15>/

01701'020040
 01702'020040
 01703'020120
 01704'044101
 01705'047124
 01706'047515
 0023 ALTKD

01707'020120
 01710'040522
 01711'044524
 01712'054440
 01713'042522
 01714'051117
 01715'051015
 01716'000000

REALP: .TXT / PARITY ERROR DETECTED<15>/

01717'020040
 01720'020040
 01721'020120
 01722'040522
 01723'044524
 01724'054440
 01725'042522
 01726'051117
 01727'051040
 01730'042105
 01731'052105
 01732'041524
 01733'042504
 01734'006400

XXI: .TXT / UNEXPECTED INTERRUPT<15>/

01735'020040
 01736'020040
 01737'020125
 01740'047105
 01741'054120
 01742'042503
 01743'052105
 01744'042040
 01745'044516
 01746'052105
 01747'051122
 01750'052520
 01751'052015
 01752'000000

WRSTAT: .TXT / NO-ERROR INTERRUPT GAVE WRONG STATUS<15>/

01753'020040
 01754'020040
 01755'020116
 01756'047455
 01757'042522
 01760'051117
 01761'051040
 01762'044516
 01763'052105
 01764'051122
 01765'052520
 01766'052040
 01767'043501
 01770'053105
 01771'020127
 01772'051117
 01773'047107
 01774'020123
 01775'052101
 01776'052125
 0024 ALTKD

01777'051415
02000'000000

IAP: .TXT / INTERRUPT ALREADY PROCESSED<15>/

02001'020040
02002'020040
02003'020111
02004'047124
02005'042522
02006'051125
02007'050124
02010'020101
02011'046122
02012'042501
02013'042131
02014'020120
02015'051117
02016'041505
02017'051523
02020'042504
02021'006400

NESE: .TXT / NO-ERROR STATUS FROM ERROR INTERRUPT<15>/

02022'020040
02023'020040
02024'020116
02025'047455
02026'042522
02027'051117
02030'051040
02031'051524
02032'040524
02033'052523
02034'020106
02035'051117
02036'046440
02037'042522
02040'051117
02041'051040
02042'044516
02043'052105
02044'051122
02045'052520
02046'052015
02047'000000

NSSE: .TXT / NO STATUS FROM ERROR INTERRUPT<15>/

02050'020040
02051'020040
02052'020116
02053'047440
02054'051524
02055'040524
02056'052523
02057'020106
02060'051117
02061'046440
02062'042522
02063'051117
02064'051040
02065'044516
02066'052105
0025 ALTKD

02067'051122
 02070'052520
 02071'052015
 02072'000000

WINT: .TXT / WRONG INTERRUPT TYPE FOR ERROR<15>/

02073'020040
 02074'020040
 02075'020127
 02076'051117
 02077'047107
 02100'020111
 02101'047124
 02102'042522
 02103'051125
 02104'050124
 02105'020124
 02106'054520
 02107'042440
 02110'043117
 02111'051040
 02112'042522
 02113'051117
 02114'051015
 02115'000000

HARDERR: .TXT / SOFT ERROR HAS HARDENED<15>/

02116'020040
 02117'020040
 02120'020123
 02121'047506
 02122'052040
 02123'042522
 02124'051117
 02125'051040
 02126'044101
 02127'051440
 02130'044101
 02131'051104
 02132'042516
 02133'042504
 02134'006400

NEWER: .TXT / NEW ERROR STATUS NOTICED<15>/

02135'020040
 02136'020040
 02137'020116
 02140'042527
 02141'020105
 02142'051122
 02143'047522
 02144'020123
 02145'052101
 02146'052125
 02147'051440
 02150'047117
 02151'052111
 02152'041505
 02153'042015
 02154'000000

.END

0026 ALTKD

AAUGH 000207'
 ABADI 001127'
 ACDAT 000100'
 AGAIN 000317'
 ALLIN 001126'
 ALLON 000047'
 ANOER 000061'
 APRO 000721'
 ARETR 001121'
 ARGEN 000113'
 ARTST 000647'
 AS 000005-
 ASIR 001123'
 ATRPC 001476'
 ATRVE 001120'
 AXER 001124'
 AXNER 001125'
 BADIN 001150'
 BIGNO 001257'
 BLKLE 001037'
 BREAK 000001'
 BRI 061002
 BUFL 001523'
 BUFSZ 001563'
 C1 000600'
 C256 000646'
 C8 000645'
 CARRY 000522'
 CDAT 000615'
 CDER 001616'
 CHRR 000077'
 CKDER 000602'
 CKDRE 000613'
 CKIER 001463'
 CKINC 001452'
 CKINT 001442'
 CKLM 001612'
 CKLV 001613'
 CMASK 001422'
 CODAD 000001-
 CPTR 000002-
 CS10 001114'
 CS2 001040'
 CS4 001041'
 CS40 001117'
 CX1 001347'
 CX2 001375'
 CX740 001346'
 CX767 001345'
 CY1 001113'
 CYL 000573'
 DASC0 000420
 DASTA 000003-
 DATA 000004
 DATF 001664'
 DB 000006'
 DBLKA 000052'
 DBMP 000010'
 DBMS 001562'
 0027 ALTKD

DBMSK 001423'
 DBUGA 001116'
 DCBEN 000015
 DCBLE 001035'
 DIR 061000
 DLEN 001036'
 DLY 001260'
 DODCB 000114'
 DSKAD 000006
 DSKBI 000353'
 DSKCO 000002
 DSKNO 000570'
 DWDCT 000713'
 DWDMX 000712'
 EFND 000253'
 EIR 061001
 ENCOD 000527'
 EOM 001556'
 EOP 001560'
 EQCOM 000440'
 EQDON 000461'
 EQU 000414'
 ERMSK 000614'
 ERROR 062000
 ESETL 001607'
 EXTRA 000456'
 FAILU 000010
 FINIS 000012
 FIRBU 001033'
 FIREL 000441'
 FL1 000465'
 FLDON 000470'
 FLUSH 000464'
 FNDIT 001226'
 GC1 000151'
 GCB 000150'
 GETQE 000165'
 GQ1 000166'
 HARDE 002116'
 HARDT 000351'
 HARDY 000256'
 HDRDI 001034'
 HDRWD 000005
 HEAD 000565'
 HEADE 000011
 HERRC 000012-
 IAD 000112'
 IAP 002001'
 IDONE 000102'
 IHDR 000107'
 IHDR1 000643'
 IMORE 000035'
 INCAD 000506'
 INCLP 000510'
 INIT 000000'
 INITA 000013'
 INTSD 000013
 INTVE 000014-
 IREE 001376'
 0028 ALTKD

IRET	001425'
ISUCN	001122'
ISULP	001064'
IVCON	000501
KBCON	000521
KBLKA	000004-
KQF	000006-
KQM	000007-
KQR	000010-
LABEL	000003
LFAIL	001641'
LIMIT	001261'
LNOTE	000632'
LOCPC	001477'
LOOK	000240'
MESSA	000000-X
MINLP	000476'
MKDCB	000124'
MKDPA	000147'
MONE	000355'
NBADI	001115'
NBP	001564'
NBUFS	001032'
NESE	002022'
NEWER	002135'
NFND	001262'
NOERR	000601'
NOKCO	000350'
NONPA	001240'
NOPAD	000110'
NOPE	001701'
NOTEM	000436'
NOTEQ	000637'
NSSE	002050'
ODSPL	001254'
OFFEN	000556'
OKCON	000347'
OLDPC	001424'
OTPC	001416'
PARCO	001255'
PARIT	001156'
PARLP	001204'
PARNX	001211'
PBUFS	001561'
PHIAD	001560'X
PLIM	001557'
PMSG	000000-
POINT	000000
PQLP	001535'
PRCT	000715'
PRMX	000714'
PRO	000722'
PULLI	000331'
R0X	001417'
R1X	001420'
R2C	000642'
R2RG	000720'
R2X	001421'
R2ZAP	000346'
0029	ALTKD

R3C 000644'
 R3CKS 001465'
 R3DOD 000123'
 R3F 000472'
 R3G 000164'
 R3MKD 000146'
 R3Q 000344'
 R3RG 000717'
 R3RU 001475'
 R3SET 001611'
 R3SL 000345'
 R3SU 001112'
 R3SUD 001031'
 R3T 000560'
 R3XX 001344'
 RBEGA 000716'
 RDBLK 000072'
 RDIT 000062'
 RDMOR 000064'
 REALP 001717'
 REDO 000031'
 REINT 001244'
 REMOV 000335'
 RES 000204'
 RESTA 000326'
 RESTH 000352'
 RETRO 001466'
 RGEN 000650'
 RGLP 000671'
 RGLPA 000674'
 RGLPO 000660'
 RGOK 000707'
 RKADR 000413'
 RR2 001473'
 RSNBO 000356'
 RSNEN 000377'
 RSNT0 000400'
 RSTBI 000354'
 RTERR 000762'
 RTLP 000742'
 RTLPA 000745'
 RTOK 000772'
 RTST 000732'
 SDBAD 000053'
 SECTC 001266'
 SECTO 000562'
 SERRC 000011-
 SERRS 000014
 SETLA 001565'
 SETLL 001603'
 SETMI 000474'
 SIR 001263'
 SIZED 001517'
 SIZEL 001503'
 SIZEM 001500'
 SIZRE 001553'
 SL10 001614'
 SLCNT 001615'
 SMAD 000111'
 0030 ALTKD

SMASH 000104'
 SOFT 000272'
 SOMEM 001554'
 SOP 001555'
 SRCHL 000215'
 STATU 000001
 STKEM 000161'
 SUBST 000101'
 SUCCE 000007
 SUDB 000775'
 SUINT 001042'
 SULP 001002'
 TABIN 000577'
 TABMA 000576'
 TABMI 000561'
 TPCP 001415'
 TRPC 000527
 TRPVE 000530
 TSULP 001047'
 UGHX 001552'
 VALID 000463'
 WHY 001252'
 WINT 002073'
 WRSTA 001753'
 WRTAL 000106'
 WRTBL 000054'
 WRTIT 000033'
 WWCON 000452
 WWLOC 000013-
 XCOM 001305'
 XER 001350'
 XER1 001332'
 XNER 001267'
 XRET 001341'
 XSHR 001333'
 XXI 001735'
 ZAPLP 000320'
 .DSPL 001253'
 .GETQ 000473'
 .RBOT 000050'
 .REST 000401'
 .RR2 000012'
 .RTOP 000051'
 .WW 001256'